

# XJ-1000FR

## Product Release



### Class "J" DSP 2-Channel Amplifier



Earthquake's XJ-1000FR is a high fidelity DSP (digital signal processing) professional amplifier. Equally suited for home and professional use, the XJ-1000FR is ideal for full range stereo reproduction and a variety of other home and studio applications.

Versatile & loaded with features, the XJ-1000FR offers users six preset equalizers: flat, music, movie, dynamic, impact, and a user mode. In user mode, a 30-band equalizer is available / programmable for ultimate sound customization. There are 4 memory storage modes that can be used to store and recall the DSP settings.

LPF (low pass filter) and HPF (high pass filter) can be set from 50Hz to 4kHz. Built-in Left / Right RCA Inputs and Left / Right XLR Balanced Inputs accommodate for a wide range of input signals; thus adding to the versatility of the XJ-1000FR.



Controls are made easy via front panel switches, via a full featured remote control, and through a computer or lap top. The included software package allows user to pre-program and change settings and functions using any computer (IBM & MAC). USB port is located on the back panel of the amplifier.

The brute power of the XJ-1000FR springs from the class "J" "Green Technology" circuitry. The Earthquake patented Class "J" combines high efficiency and power (1000 Watts RMS / 4-Ohms bridged).

#### Features:

- Full Featured Remote Control with: ON/OFF control / Function keys / Mute control / Preset EQ modes Selector / Store hot key / Recall hot key
- USB Port: for operating the amplifier and / or uploading new firmware (PC & MAC ready).
- Protection & Clip LED
- LCD Display Module
- Encoder Switch: controls the operation of the functions.
- Left/ Right RCA Inputs and Left/ Right XLR Balanced Inputs
- Stereo / Bridged Switch
- 30 bands of equalization
- External Trigger 12VDC Input

#### Specifications:

- Power Output: 1 x 1000 Watts RMS @ 4-Ohms bridged  
1 x 600 Watts RMS @ 8-Ohms bridged  
2 x 300 Watts RMS @ 4-Ohms stereo  
2 x 150 Watts RMS @ 8-Ohms stereo  
2 x 500 Watts RMS @ 2-Ohms stereo
- Size & Weight: H=1-3/4" x W=17" x D=13-1/4" (45mm x 432mm x 337mm)  
13.52 lbs / 6.15 Kg

XJ-1000FR

**MSRP**  
**\$1499.00**

