


Upsonic Power Features Chart

Supplier	Model	Capacity VA / Watts	UPS Warranty	Battery Warranty	LCD Display	Rack (R) or Tower (T)	Line Interactive AVR (Auto Voltage Regulator)	True On-Line	Double Conversion Technology	SineWave Output	Power Outlets Number & Type	Surge Filtration Telephone / Modem	Built in Comms	Optional (SNMP) (Relay) etc. Network Cards	Battery Quantity	Battery Type	DC Voltage	Supplied Without Battery order with Main Unit	Extended Runtime Battery Available	15 Amp Socket or Hardwire Connection Required
UPSONIC	Orion 750	750 / 450	3 yr.	2 yr.	No	T	YES	NO	NO	Simulated	3 x Aus 3-Pin 2 x Extra Surge Only	RJ 45	USB/RS232	No	1	12V / 9AH	12	NO	NO	NO
UPSONIC	DS 600	600 / 360	3 yr.	2 yr.	YES	T	YES	NO	NO	Modified	2 x AUS 3-Pin	RJ 11	USB/RS232	NO	1	12V / 7AH	12	NO	NO	NO
UPSONIC	DS 800	800 / 480	3 yr.	2 yr.	YES	T	YES	NO	NO	Modified	2 x AUS 3-Pin	RJ 11	USB/RS232	NO	1	12V / 9AH	12	NO	NO	NO
UPSONIC	DS 1000	1000 / 600	3 yr.	2 yr.	YES	T	YES	NO	NO	Modified	3 x AUS 3-Pin	RJ 45	USB/RS232	NO	2	12V / 7AH	12	NO	NO	NO
UPSONIC	DS 1400	1400 / 840	3 yr.	2 yr.	YES	T	YES	NO	NO	Modified	3 x AUS 3-Pin	RJ 45	USB/RS232	NO	2	12V / 9AH	12	NO	NO	NO
UPSONIC	DS 2000	2000 / 1080	3 yr.	2 yr.	YES	T	YES	NO	NO	Modified	3 x AUS 3-Pin	RJ 45	USB/RS232	NO	2	12V / 9AH	12	NO	NO	NO
UPSONIC	ES 1RU 10	1000 / 625	3 yr.	2 yr.	YES	R / T	YES	NO	NO	TRUE	4 x IEC	RJ11	USB/RS232	YES	4	6V / 9AH	24	NO	NO	NO
UPSONIC	ES 1RU 15	1500 / 938	3 yr.	2 yr.	YES	R / T	YES	NO	NO	TRUE	4 x IEC	RJ11	USB/RS232	YES	4	6V / 9AH	24	NO	NO	NO
UPSONIC	EST 10	1000 / 625	3 yr.	2 yr.	YES	T	YES	NO	NO	TRUE	3 x IEC	RJ11	USB	YES	2	12V / 7AH	24	NO	NO	NO
UPSONIC	EST 15	1500 / 938	3 yr.	2 yr.	YES	T	YES	NO	NO	TRUE	3 x IEC	RJ11	USB	YES	3	12V / 7AH	36	NO	NO	NO
UPSONIC	EST 20	2000 / 1250	3 yr.	2 yr.	YES	T	YES	NO	NO	TRUE	6 x IEC	RJ11	USB	YES	3	12V / 9AH	36	NO	NO	NO
UPSONIC	ESRT 10	1000 / 625	3 yr.	2 yr.	YES	R / T	YES	NO	NO	TRUE	6 x IEC	RJ11	USB/RS232	YES	2	12V / 7AH	36	NO	NO	NO
UPSONIC	ESRT 15	1500 / 938	3 yr.	2 yr.	YES	R / T	YES	NO	NO	TRUE	6 x IEC	RJ11	USB/RS232	YES	3	12V / 7AH	36	NO	NO	NO
UPSONIC	ESRT 20	2000 / 1250	3 yr.	2 yr.	YES	R / T	YES	NO	NO	TRUE	6 x IEC	RJ11	USB/RS232	YES	3	12V / 9AH	36	NO	NO	NO
UPSONIC	ESRT 30	3000 / 1875	3 yr.	2 yr.	YES	R / T	YES	NO	NO	TRUE	10 x IEC	RJ11	USB/RS232	YES	6	12V / 7AH	36	NO	NO	15 amp
UPSONIC	ESRT 50	5000 / 3125	3 yr.	2 yr.	YES	R / T	YES	NO	NO	TRUE	10 x IEC + TB	RJ11	USB/RS232	YES	8	12V / 9AH	48	NO	NO	Hardwire (32amp)
Note: ESLR Series requires ESBP 3RU Long Runtime Battery Pack - Units do not have Battery Fitted - Must be Purchased at time of ordering Main Unit																				
UPSONIC	ESLR 10	1000 / 625	3 yr.	2 yr.	YES	R / T	YES	NO	NO	TRUE	6 x IEC	RJ11	USB/RS232	YES	0	24V / 7AH	24	YES	YES	NO
UPSONIC	ESLR 15	1500 / 938	3 yr.	2 yr.	YES	R / T	YES	NO	NO	TRUE	6 x IEC	RJ11	USB/RS232	YES	0	24V / 7AH	36	YES	YES	NO
UPSONIC	ESLR 20	2000 / 1250	3 yr.	2 yr.	YES	R / T	YES	NO	NO	TRUE	6 x IEC	RJ11	USB/RS232	YES	0	24V / 7AH	36	YES	YES	NO
UPSONIC	ESLR 30	3000 / 1875	3 yr.	2 yr.	YES	R / T	YES	NO	NO	TRUE	10 x IEC	RJ11	USB/RS232	YES	0	36V / 7AH	36	YES	YES	15 amp
UPSONIC	ESLR 50	5000 / 3125	3 yr.	2 yr.	YES	R / T	YES	NO	NO	TRUE	5 x IEC + TB	RJ11	USB/RS232	YES	0	48V / 9AH	48	YES	YES	Hardwire (32amp)
UPSONIC	ESLR 75	7500 / 4688	3 yr.	2 yr.	YES	R / T	YES	NO	NO	TRUE	5 x IEC + TB	RJ11	USB/RS232	YES	0	48V / 9AH	48	YES	YES	Hardwire (50amp)
UPSONIC	IS 1000	1000 / 700	3 yr.	2 yr.	YES	T	NO	YES	YES	TRUE	3 x IEC / 1 x AUS	RJ 45	RS322	YES	3	12V / 7AH	36	NO	NO	NO
UPSONIC	IS 2000	2000 / 1400	3 yr.	2 yr.	YES	T	NO	YES	YES	TRUE	3 x IEC / 2 x AUS	RJ 45	RS322	YES	6	12V / 9AH	72	NO	NO	NO
UPSONIC	IS 3000	3000 / 2100	3 yr.	2 yr.	YES	T	NO	YES	YES	TRUE	Hardwire / 2 x AUS	RJ 45	RS322	YES	8	12V / 9AH	96	NO	NO	15 amp
UPSONIC	IRT 1000	1000 / 700	3 yr.	2 yr.	YES	R/T	NO	YES	YES	TRUE	3 x IEC / 1 x AUS	RJ 45	RS322	YES	3	12V / 7AH	36	NO	YES	NO
UPSONIC	IRT 2000 2U	2000 / 1400	3 yr.	2 yr.	YES	R/T	NO	YES	YES	TRUE	6 x IEC	RJ 45	RS322	YES	6	12V / 9AH	72	NO	YES	NO
UPSONIC	IRT 2000 4U	2000 / 1400	3 yr.	2 yr.	YES	R/T	NO	YES	YES	TRUE	4 x Aust 3 pin	RJ 45	RS322	YES	6	12V / 9AH	72	NO	YES	NO
UPSONIC	IRT 3000 2U	3000 / 2100	3 yr.	2 yr.	YES	R/T	NO	YES	YES	TRUE	6 x IEC	RJ 45	RS322	YES	6	12V / 9AH	72	NO	YES	15 amp
UPSONIC	IRT 3000 4U	3000 / 2100	3 yr.	2 yr.	YES	R/T	NO	YES	YES	TRUE	4 x Aust 3 pin	RJ 45	RS322	YES	6	12V / 9AH	72	NO	YES	15 amp
UPSONIC	IRT 3000 LR 4U	3000 / 2100	3 yr.	2 yr.	YES	R/T	NO	YES	YES	TRUE	Hardwire / 2 x AUS	RJ 45	RS322	YES	6	12V / 9AH	72	NO	YES	15 amp

Please Note: The above matrix has been supplied to use as a guide only features are subject to change without notification - IMPORTANT When configuring units for extra runtime (backup) please contact Upsonic Power to confirm solution as runtime can / may vary due to the environment that the UPS will be located and operated with-in along with the devices the UPS is required to support. Please refer to Autonomy Sheet for approx Runtime (Watts v Runtime).

Contact Information: Wayne Dennis 0417 536 007 wayned@upsonic.com.au
 Peter Barnett 0423 840 686 peterb@upsonic.com.au
 Rick Mezzetta 0423 840 687 rickm@upsonic.com.au
 Upsonic Power Pty Ltd 03 9706 0045
 Website www.upsonic.com.au



Is your businesses critical data and equipment protected?

Please Note: Not all models and views are presented. Comprehensive brochures are available on our website www.upsonic.com.au

